



## Radio Remote Control 2 Channels 2 Speed Multi voltage Range 300 ft

### Características Esenciales

- 200 Auto Channels replacing traditional single channel quartz plus 1 Million ID Codes.
- Easy Pairing System, no need of software or copier to add or replace lost or broken Transmitter
- Customizable 200 Functions settings to meet any special requirements
- Reinforced fiber plastic case for Transmitter and Receiver plus rubber protector for Transmitter

### Especificaciones Técnicas

<b>Transmitter Emergency Stop</b>	Yes	<b>Control Speed</b>	2 Speed
<b>Channels</b>	2	<b>Código FCC</b>	2AZMK-Q1212
<b>Botones</b>	3	<b>Fuente de Alimentación del Transmisor</b>	2 AA batteries
<b>Fuente de Alimentación del Receptor</b>	AC 110V-480V	<b>Sensibilidad del Receptor</b>	dBm -112
<b>Distancia de Control</b>	300 ft / 100 mt	<b>Código de Seguridad</b>	200 Millions
<b>Potencia del Transmisor</b>	≤10dBm	<b>Rango de Frecuencia</b>	433/480 MHz
<b>Rango de temperatura de Trabajo</b>	-40 ~ 185 °F / -40 ~ 85°C	<b>Normas</b>	FCC and OSHA standard 1910.179
<b>Garantía</b>	1 Year	<b>Wireless Control IP Protection</b>	IP65

## Peso & Dimensiones

**Peso Total** 4 lbs / 2 Kg

## Detalles del Empaque

**A Altura Total** 5.3

**D Depth** 1.2

**W Ancho** 2.7

Referential Images / Imágenes Referenciales  
Specifications may change without notice / las especificaciones pueden cambiar sin previo aviso